rutec Licht GmbH & Co. KG | Carl-Zeiss-Str. 15 | 28857 Syke
TEL +49 (0) 42 42 95 65 - 0 | FAX +49 (0) 42 42 95 65 - 25 | E-MAIL INFO@RUTEC.DE | WWW.RUTEC.DE



100-240V LED Konverter 1000mA 34W-48W

Article nr.: 85990

rutec LED constant current converters · for indoor use · · Built-in active power factor connection (active PFC) · IP64 · Protection Class 2, CE, RoHS, REACH · Protection against short-circuit, overtemperature and overcurrent · Primary and secondary-sided 1 supply and feed line · · SECONDLIFE ITEM -heavily discounted- only while stocks last!

TECHNICAL DATA

Unit Code	pcs
BAR code	4012094859903
Housing colour	Weiss
Length	163.00 mm
Width	45.00 mm
Height	33.00 mm
Lamp	without
IP rating	64
Power	34-48 W
Current mA	1000 mA

rutec Licht GmbH & Co. KG | Carl-Zeiss-Str. 15 | 28857 Syke

TEL +49 (0) 42 42 95 65 - 0 | FAX +49 (0) 42 42 95 65 - 25 | E-MAIL INFO@RUTEC.DE | WWW.RUTEC.DE



100-240V LED Konverter 1000mA 34W-48W

Article nr.: 85990

TECHNICAL DATA

Input voltage	100-240
Output voltage	34-48
Material	Kunststoff
Tollerance	5.00
Efficiency	88.00
Temperature range	-30 - 50
Suitable light source	