rutec Licht GmbH & Co. KG | Carl-Zeiss-Str. 15 | 28857 Syke
TEL +49 (0) 42 42 95 65 - 0 | FAX +49 (0) 42 42 95 65 - 25 | E-MAIL INFO@RUTEC.DE | WWW.RUTEC.DE



f.80450 Funkhandsender 2-Kanal Select 4 ZONEN

Article nr.: 80576

rutec RF hand transmiter has up to 4 zones and is suitable for · two-colour (Select) receiver · for indoor use · Material: plastic · IP20 · CE, REACH, RoHS · Voltage: 3x AAA battery (not included in scope of delivery) · Remote control range: 30 metres with cler view · Carrier frequency: 868 MHz · Dimmer range 0,1 - 100% · with memory effect · Control up to 4 zones independently · highly sensitive touch colour wheel · fast and precise color or brightness control · dimming and switching of single and mixed colors · per zone: 3 short-cut keys for individual light scenes · including magnetic wall holder for srewing or mounting · with self adhesive backside

TECHNICAL DATA

Unit Code	pcs
BAR code	4012094805764
Housing colour	Schwarz
Length	120.00 mm
Width	55.00 mm
Height	17.00 mm
Lamp	without
IP rating	20
Input voltage	4,5
Material	Kunststoff

rutec Licht GmbH & Co. KG | Carl-Zeiss-Str. 15 | 28857 Syke

TEL +49 (0) 42 42 95 65 - 0 | FAX +49 (0) 42 42 95 65 - 25 | E-MAIL INFO@RUTEC.DE | WWW.RUTEC.DE



f.80450 Funkhandsender 2-Kanal Select 4 ZONEN

Article nr.: 80576

TECHNICAL DATA

Efficiency	98.00
Temperature range	-20 - 50
Suitable light source	