



144W/288W Vardaflex einfarbig Slave Funkempfänger 12/24V

Article nr.: 89451

LED Wireless Controller Constant Voltage 12 V-24 V · IP20 · Wireless Receiver with Dimmer (up to 25% Brightness) and Controller Function for · the Control of Single-Color and RGB LEDs With Common Anodes. · for Indoor Use · RGB Version: 8 Preset Colors, More than 1000 Adjustable Colors; Color Changes · Possible at Any Time, Automatic Color Change Cycle (Adjustable); Each Color · Dimmable, 3 Scenes at Any Time · Receiving Frequency: 868,3 MHz · Maximum Cross Section for the Button Input and Output: 1,5 sq mm · Master and Slave Must be Connected by the Cable. · For Slave Devices a 15 cm Cable is Included in the Delivery. · Remote Control Required · Push Button Control is Possible · Made in EU · Detailed Information for DMX / DALI Controllers · SECONDLIFE ITEM -heavily discounted- only while stocks last!

TECHNICAL DATA

Unit Code	pcs
BAR code	4012094894515
Length	165.00 mm
Width	47.00 mm
Height	35.00 mm
Lamp	without
IP rating	20
Power	144-288 W
Current mA	12000 mA
Input voltage	12-24





 Secondlife-Shop

144W/288W Vardaflex einfarbig Slave Funkempfänger 12/24V

Article nr.: 89451

TECHNICAL DATA

Output voltage	12-24
Material	Kunststoff
Temperature range	-20 - 50
Suitable light source	

