




144W/288W RGB Master Funkempfänger 12/24V

Article nr.: 89460

LED Wireless Controller Constant Voltage 12 V-24 V · IP20 · Wireless Receiver with Dimmer (up to 25% Brightness) and Controller Function for · the Control of Single-Color and RGB LEDs With Common Anodes. · for Indoor Use · RGB Version: 8 Preset Colors, More than 1000 Adjustable Colors; Color Changes · Possible at Any Time, Automatic Color Change Cycle (Adjustable); Each Color · Dimmable, 3 Scenes at Any Time · Receiving Frequency: 868,3 MHz · Maximum Cross Section for the Button Input and Output: 1,5 sq mm · Master and Slave Must be Connected by the Cable. · For Slave Devices a 15 cm Cable is Included in the Delivery. · Remote Control Required · Push Button Control is Possible · Made in EU · Detailed Information for DMX / DALI Controllers · SECONDLIFE ITEM -heavily discounted- only while stocks last!

TECHNICAL DATA

Unit Code	pcs
BAR code	4012094894607
Length	165.00 mm
Width	47.00 mm
Height	35.00 mm
Depth in ceiling	35.00 mm
Lamp	without
IP rating	20
Power	144-288 W
Current mA	12000 mA





 Secondlife-Shop

144W/288W RGB Master Funkempfänger 12/24V

Article nr.: 89460

TECHNICAL DATA

Input voltage	12-24
Output voltage	12-24
Material	Kunststoff
Temperature range	-20 - 50
Suitable light source	

