




144W/288W RGB Funksyncron Slave Funkempfänger 12/24V

Article nr.: 89466

LED Wireless Controller Syncro Constant Voltage 12 V-24 V · IP20 · Wireless Receiver with Dimmer (up to 25% Brightness) and Controller Function for · the Control of Single-Color and RGB LEDs with Common Anodes. · For Indoor Use · RGB Version: 8 Preset Colors LED, Adjustable to More Than 1000 Colors; Color · Changes are Possible at Any Time; Automatic Color Change Cycle (Adjustable); · Every Color is Dimmable; 3 Scenes Available at Any Time · Receiving Frequency: 868,3 MHz · Maximum Cross Section for the Button Input and Output: 1,5 sq mm · Remote Control Required · Master and Slave are Wirelessly Connected · Push Button Control is Possible · Made in EU · Maximum One System per Household · SECONDLIFE ITEM -heavily discounted- only while stocks last!

TECHNICAL DATA

Unit Code	pcs
BAR code	4012094894669
Length	165.00 mm
Width	47.00 mm
Height	35.00 mm
Lamp	without
IP rating	20
Power	144-288 W
Current mA	12000 mA
Input voltage	12-24





 Secondlife-Shop

144W/288W RGB Funksyncron Slave Funkempfänger 12/24V

Article nr.: 89466

TECHNICAL DATA

Output voltage	12-24
Material	Kunststoff
Temperature range	-20 - 50
Suitable light source	

