rutec Licht GmbH & Co. KG | Carl-Zeiss-Str. 15 | 28857 Syke
TEL +49 (0) 42 42 95 65 - 0 | FAX +49 (0) 42 42 95 65 - 25 | E-MAIL INFO@RUTEC.DE | WWW.RUTEC.DE



PIR Sensor Controller Stair Light für VARDAflex LED-Controller, ES32, inkl. 3 Sensoren, max. 32 St.

Article nr.: 80603

LED staircase lighting controller for up to 32 steps, individually controllable · for indoor use, IP20 · 32 channels, 1 A · protection class III, CE, RoHS · input: 5 V - 24 V DC · output: 5 V - 24 V DC (PWM) · power: 160 W (5 V), 384 W (12 V), 768 W (24 V) · LxWxH in mm: 186 x 86 x 25.5 · with 2 PIR sensors and a brightness sensor · several programmes and push button function can be called up · temperature range: -30°C to +40°C · scope of delivery: 1 LED staircase lighting controller, 2 PIR sensors with 1.2 m cable, 1 · brightness sensor with 0.3 m cable, 2 extensions cables 5 m for PIR sensor · Laser engraving of the logo is only possible with a minimum order quantity of 1000 pieces.

TECHNICAL DATA

Unit Code	pcs
BAR code	4012094806037
Housing colour	Weiss
Length	186.00 mm
Width	86.00 mm
Height	25.50 mm
Lamp	without
IP rating	20
Power	160-768 W
Current mA	32000 mA



rutec Licht GmbH & Co. KG | Carl-Zeiss-Str. 15 | 28857 Syke

TEL +49 (0) 42 42 95 65 - 0 | FAX +49 (0) 42 42 95 65 - 25 | E-MAIL INFO@RUTEC.DE | WWW.RUTEC.DE



PIR Sensor Controller Stair Light für VARDAflex LED-Controller, ES32, inkl. 3 Sensoren, max. 32 St.

Article nr.: 80603

TECHNICAL DATA

Input voltage	5-24
Output voltage	5-24
Material	Stahl
Temperature range	-30 - 55
Suitable light source	

rutec Licht GmbH & Co. KG | Carl-Zeiss-Str. 15 | 28857 Syke
TEL +49 (0) 42 42 95 65 - 0 | FAX +49 (0) 42 42 95 65 - 25 | E-MAIL INFO@RUTEC.DE | WWW.RUTEC.DE



PIR Sensor Controller Stair Light für VARDAflex LED-Controller, ES32, inkl. 3 Sensoren, max. 32 St.

Article nr.: 80603

TECHNICAL DRAWING

